INV2000 Inverter Generator

UK (522-2699)



1800 W Rated | 2000 W Maximum

Features

- Quiet operation great for camping and caravanning
- DOUBLE your power by paralleling with another INV2000
- Clean, regulated A/C power for sensitive electronics (<3% THD)
- 2x USB Ports, including a 2.1 Amp port for charging your tablet
- Intuitive single start/stop switch with integrated choke



Because of continuing improvements, actual product may differ slightly from this photo.

Control Panel



INV2000 Inverter Generator

UK (522-2699)



Specifications

ENGINE	
Starting Method	Recoil
Run Time @ 50% Load	6 hours
Idle Control	Engine Smart Control (ESC)
Fuel Tank Nominal Capacity	4 L
Fuel Tank Material	Plastic
Fuel Type	Unleaded Petrol
Fuel Gauge	Dial Gauge
Engine Displacement	79.7 cc
Engine Type	OHV
Engine Speed	Variable RPM
Lubrication Method	Splash
Recommended Oil	SAE 30 / 10W-30
Oil Capacity	0.380 L
Region Certifications	CE
Shutdown Method	Automatic Low Oil Level

ELECTRICAL	
Rated Power	1800 Watts
Maximum Power	2000 Watts
AC Output	240V (230V) @ 50 Hz
DC Output	12V (8.3A) / 5V (2.1A)
Total Harmonic Distortion (THD)	< 3%
Receptacles	2x 230V 13A
	1x 5V 2.1A USB
	1x 5V 1.0A USB
	1x 12V DC 8.3A
Voltage Regulation	Inverter Type

EXTRA FEATURES	
Illuminated Control Panel	Yes
Handle Style	Integrated
Indicator Lights	Low Oil and Overload
USB	1x 2.1A 5V
	1x 1.0A 5V


WARRANTY


3-year limited

Dimensions and Weights

ASSEMBLED	
Height	460 mm
Width	497 mm
Length	318 mm
Extended Length	-
Unit Weight	22.1 kg

CARTON		
Height	545 mm	
Width	610 mm	
Length	406 mm	
Shipping Weight	26 kg	





Accessories

INV2000 Parallel Kit (530-1203)



INV2000 Cover (530-1204)



CATERPILLAR®



